

Be sure to install the correct binary; at the moment each there is a different binary for the G, H, and J releases of Guardian.

For G Series - OFFENDER-G.EXE
For H Series - OFFENDER-H.EXE
For J Series - OFFENDER-J.EXE

- 1) Save the appropriate version on your PC.
- 2) FTP the OFFENDER EXE in BINARY mode to \$SYSTEM.OFFENDER.OFFENDER.

The files are NSK program files.

FTP the license file in BINARY mode to \$SYSTEM.OFFENDER.LICENSE

Log on to the HP NonStop server as a Super Group user and run the following commands

```
-- Use 700 on G Series and 800 on H and J Series
FUP alter $system.offender.offender, code 700
-- Use NUNU if you want to give all users access to offender otherwise use GUGU
FUP secure $system.offender.offender, GUGU, progid
```

Logoff

Current Release

OmniOffender Version 2.2.1

```
S-Series T0658G06^17NOV08
H-Series T0658H06^17NOV08
J-Series T0658J06^17NOV08
```

Enhancements/Fixes:

- 1) Fixed ABEND when license check fails

Known problems:

- 1) Warning limits/rates need adjusting.
- 2) Several displayed items are based on 32 bit counters which may overflow.
- 3) 'CPU IPC' send busy and the message size statistics are all displayed as 0.
- 4) 'CPU BAR' display is garbled when the output line is 80 characters or greater. The display will correct itself when a short line is written.
- 5) No event is logged when OmniOffender terminates due to a hard error on the IN or OUT file.
- 6) When using MR-Win6530 and the GO command, the display will not home correctly unless conversational mode is disabled (a Win6530 bug).

Past Release Enhancements/Fixes

OmniOffender Version 2.2

```
S-Series T0658G06^26AUG08
H-Series T0658H06^26AUG08
J-Series T0658J06^26AUG08
```

Enhancements/Fixes:

- 1) Changed to use standard Opsol License files

OmniOffender Version 2.1

S-Series T0658G06^24JUL08

H-Series T0658H06^24JUL08

J-Series T0658J06^24JUL08

Enhancements/Fixes:

- 1) Support for J-Series
- 2) Added CPU IPU option (H & J Series only)
- 3) Added CPU TMF option
- 4) Added Quit command
- 5) ENV command will report OS release and offender version
- 6) Default option for Cpu, Disc, File and PR commands
- 7) reports will print in the order input
- 8) Receive queue value is correctly displayed (previously 0 was displayed)
- 9) A hard error on IN or OUT file will no longer create a save file